

INSTALLATION INSTRUCTION

Atmosphere 4.5" - Remodel Housing

A1RB-3661, A1RB-3662, A1RB-3663



SAFETY INSTRUCTION

IMPORTANT: Never attempt any work without shutting off the electricity.

- Read all instructions before installing.
- System is intended for installation by a qualified electrician in accordance with the National Electrical Code and local regulations.
- Go to the main fuse box, or circuit breaker. Place the main power switch in the "OFF" position and unscrew the fuse(s) or switch "OFF" the circuit breaker switch(es) that control the power to the fixture or room that you are working on.
- Place the wall switch in the "OFF" position.

AVERTISSEMENT

IMPORTANT: Coupez l'électricité avant TOUTE manipulation.

- Lisez toutes les instructions avant d'installer.
- Système est destiné à être installé par un électricien qualifié en conformité avec le code national de l'électricité et les règlements locaux.
- Accédez au panneau central de disjoncteurs ou de fusibles de votre demeure et placez l'interrupteur principal en position d'arrêt (« OFF »).
- Placez l'interrupteur mural en position d'arrêt (« OFF »).


CAUTION:

All parts must be used as indicated in these instructions. Do not substitute any parts, leave parts out, or use any parts that are worn out or broken. Failure to follow this instruction could invalidate the ETL/cETL listing of this fixture.

OVERVIEW:

Housing is remodel. Housing requires a trim for a finished look. Refer to specification sheets for compatible trim options.

OVERALL HOUSING DIMENSION



SPECIFICATIONS	
Input:	120-277V, 50/60Hz
Installation:	Non-IC
Dimming	DMX for CT-X model 0-10V for CT-Z model

AISPIRE retains the right to modify the design of our products at any time as part of the company's continuous improvement program.

INSTALLATION INSTRUCTION

Atmosphere 4.5" - Remodel Housing

A1RB-3661, A1RB-3662, A1RB-3663

FIG. 1




FIG. 2




FIG. 3





FIG. 4



HOUSING INSTALLATION:

- At the point of installation, cut a 5 1/8" round hole for a round trim or a 5 1/8" X 5 1/8" square hole for a square trim (See **FIG. 1**).

Note: Ceiling thickness table below:

Trim Model	Trim Description	Ceiling Thickness		
		1/2"	1"	1 1/2"
A1RB-D	Downlight	Yes	Yes	Yes
A1RB-S	Shallow Regressed Downlight	Yes	Yes	Yes
A1RB-A	Adjustable	Yes, to 45°	Yes, to 45°	Yes, to 35°
A1RB-W	Wall Wash	Yes	Yes	No

- Pull building supply wires through ceiling cutout and open fixture junction box door (See **FIG. 2**).

Remove desired housing knockout and feed building wires into housing using appropriate connector.

- Connect fixture wires to building wires: insert each supply wire into appropriate connector.

- For 0-10V control [**CT-Z** models] (See **FIG. 3**): Two 0-10V input signals are used to achieve CCT and intensity changing. Recommended maximum of 500ft of 18 ga 0-10V communication wiring.
- For DMX control [**CT-X** models] (See **FIG. 4**): Two DMX input channels are used to achieve CCT and intensity changing. Factory default Channel 1 is CCT changing and Channel 2 is intensity changing. If differing channels are desired in the field, use of a RDM compatible control console can reassign channels.

It is recommended to use cable specifically designed for DMX. These cables have an impedance of 120Ω and a low capacitance. For instance: Belden 9841 or 3105a. At the last fixture, the cable to be terminated with a 120Ω resistor between the DMX (+) and DMX (-) pinouts to prevent reflections of the signal. The resistor value of the resistor on the last driver should be kept the same as the resistor of signal wires.

Recommended maximum of 500ft of cabling from controller to last fixture.
After 32 unit loads a repeater/booster is recommended.


INSTALLATION INSTRUCTION

Atmosphere 4.5" - Remodel Housing

A1RB-3661, A1RB-3662, A1RB-3663


AiSPIRE
A W A C C O M P A N Y

FIG. 5



4. Place all wiring and connectors back in junction box and replace the junction box's cover (See **FIG. 5**).

FIG. 6



5. Guide junction box through the cut hole and secure appropriately (See **FIG. 6**).
6. Refer to installation instructions for appropriate trims to complete the installation.

AiSPIRE retains the right to modify the design of our products at any time as part of the company's continuous improvement program.